

*Application*  
*for*  
*United States Letters Patent*

*To all whom it may concern:*

*Be it known that,*

*Neil Roy HINSON*

*have invented certain new and useful improvements in*

*A VIDEO EDITING SYSTEM*

*of which the following is a full, clear and exact description:*

006250-9862500

## A Video Editing System

The invention relates to a video editing system.

There are several different broadcast standards for television widely in use around the world. Of these, one is the so-called NTSC standard used in the United States in which television pictures are broadcast at a rate of 30 frames per second, two interleaved fields per frame and 525 lines per frame, and another is the so-called PAL standard used in Europe in which pictures are broadcast at 25 frames per second, two interleaved fields per frame and 625 lines per frame. Movies are captured on film at a rate of 24 frames per second. Top selling television programmes for example "episodics" such as the American television series "ER" are also shot on film at the 24 frames per second rate. Once scenes have been shot the film frames are transferred into an electronic domain by way of a telecine machine.

Plainly, there is an incompatibility between the 24 frames per second of film and the 25 PAL frames and 30 NTSC frames of television. This incompatibility is overcome in one of two ways. If the film is to be shown on NTSC television the film is run through the telecine at 24 frames per second and the film frames are scanned as two television fields. The 24 frames are converted to 30 frames by outputting the first field of the first frame, then the second field and then the first field again. Next, the second field of the second frame is output, then the first. For the third frame the second field is output, then the first and then the second, and for the fourth frame the first

field is output first followed by the second. This pattern is repeated for the next group of four frames. The result of this is that 24 film frames (corresponding to one second of moving image) lasts for 60 television fields (also corresponding to one second of moving image). This technique is known as 3:2 pull down and is described for example in our British Patent Application No. 9209204.8 and corresponding US Patent No. 5418572, the teachings of which are incorporated herein by reference.

In both the NTSC and the PAL broadcast standards each television frame comprises two interleaved frames. One field comprises all the odd numbered lines in a frame and the other field comprises all the even numbered lines in a frame. If the film is to be viewed on a PAL system at 25 frames per second each film frame is scanned twice (once for each television frame) by the telecine. Frames are output from the telecine at a rate of 25 per second. As a result, when the television signals are displayed, once second of film (24 frames) only lasts for 0.96 seconds of television. The speed of action and dynamics in the picture are increased and sound is heard at a slightly higher pitch. Movies and programmes originating on film have always been viewed in this way on PAL televisions.

While these two approaches provide an adequate solution to frame rate incompatibility, they are nevertheless separate operations and it is not possible satisfactorily to convert films or programmes between NTSC and PAL if they have already been converted from the 24 frame movie format to the 25 or 30

frame format of PAL or NTSC. Simply converting from one television standard to the other introduces unacceptable artifacts as the frame rate is changed between 25 and 30 per second and the line rate is changed between 525 and 625 per frame. One way of overcoming this problem is to carry out the editing twice, once to convert from film to NTSC and once to convert from film to PAL. Plainly this is undesirable because it is difficult (dynamics are different at a frame level between the two standards), the effects applied in one standard have to be applied again in the other standard, and costs are increased significantly.

There has recently been a move towards making a single 625 line master tape. The approach that has been adopted is to use a conventional tape-based edit suite with a standard 25/625 VTR adapted so that it is able to record and play the same tape at either the standard 25 frames per second or at a slower 24 frames per second and 625 lines per frame. During the editing process the moving picture is viewed at the correct pace of 24 frames per second and thus the dynamics in the picture are also seen correctly. Once a satisfactory edit has been created and stored on tape, the tape is simply played back at 25 frames per second (4 percent faster than real image time) to give the correct 25/625 rate for PAL.

When an NTSC master tape is required the edited clip is output at 24 frames per second to circuitry which converts the 625 lines to 525 lines and converts the 24 frames per second into 30 frames per second using 3:2 pull

5

10

15

20

5

10

Again, while this approach is able to produce satisfactory results, it is nevertheless laborious, difficult and thus expensive to produce separate 25/625 and 30/525 distribution copies from a single master.

15

According to the invention there is provided an editing system for moving images, the editing system comprising: a frame-random access store for storing image data representing a sequence of image frames which together form a moving image, the store storing data such that the frames can be accessed in a random order; an input circuit for receiving from a source data representing one or more sequences of image frames captured at a first frame rate, the data being received at an input data rate and representing each frame in a sequence as a first multiplicity of image lines which together form the image frame, and for transferring the data to the frame-random access

store; an editing processor for editing data read from the store at a processed data rate to produce data representing an edited sequence of image frames; and an output circuit for outputting edited data representing an edited sequence of image frames at a second frame rate, the data being output at an output data rate and representing each frame in the edited sequence as a second multiplicity of image lines which together form the image frame.

The invention also provides an editing system in which image data representing an initial moving image input in a first format at a corresponding rate is stored in a store and is manipulated to produce image data representing an edited moving image for output in a second format at a corresponding data rate, the system being arranged such that processing is effected at a data rate which is variable and determines the second data rate.

The above and further features of the invention are set forth with particularity in the appended claims and together with advantages thereof will become clearer from consideration of the following detailed description of an exemplary embodiments of the invention given with reference to the accompanying drawings.

In the drawings:

Figure 1 is a schematic functional block diagram of a system embodying the invention;

Figure 2 is a schematic functional block diagram of another system embodying the invention.

Turning now to Figure 1 of the accompanying drawings there is shown a video editing system 1 comprising a frame-random access data store (represented by the broken lines 2) connected to receive video data via an input butter 3 (suitably a FIFO buffer) from one or more video sources, for example a telecine 4 or a video tape recorder (VTR) 5. Both the telecine 4 and the VTR 5 are standard video data sources designed to supply data representing video frames at a predetermined frame rate, with each frame comprising a predetermined number of lines per frame.

Movie cameras are designed to capture movie images on film at a rate of 24 frames per second. The telecine 4 is designed to scan each frame of the film clip into a predetermined number of lines and to output that data in the format of 25 frames per second, 2 interleaved fields per frame and 625 lines per frame. Thus the telecine 4 generates video data representing image frames from a film clip 6. The VTR 5 is also designed to output video data in the format of 25 frames per second with two interleaved fields together comprising a total of 625 lines per frame. This will be referred to herein as the 25/625 format. Both the telecine 4 and the VCR 5 are standard pieces of equipment and need not be described in any greater detail herein.

Figure 1 shows the telecine 4 connected to the VTR 5, because this is the normal route by which data would be supplied from a telecine to an editing system. There is however no technical reason why the telecine 4



should not be connected directly to the input buffer 3 to input data to the frame-random access data store 2.

The frame-random access store 2 is a large data storage device capable of storing data representing video frames in frame-random access order. That is to say, the data representing any frame stored in the store can be accessed as quickly as the data representing any other frame in the store. Typically the store comprises a number of disk stores 7 connected to RAM or other buffers 8 and to data interfaces and highways which together enable video data to be output therefrom at a rate (for example the 25/625 rate) determined by a system clock 10. The system clock 10 is arranged to generate a clocking signal representing the frame rate (e.g. 25 per second) of the video data. Transfers of data around the system 1 are synchronised to the clocking signal so that, for example, 25 frames of data are input to or output from the store 2 in each second. The store 2 may also comprise a sizing circuit 11 for changing the size of frames of data, for example, from 625 lines to 525 lines per frame. The sizing circuit 11 comprises an interpolator and is connected to change the size of data output from the disk stores 7 before the data is input to the RAM buffers 8. The store 2 may be based on the data storage apparatus described in our British Patent Application No. 9226199.9 published as GB-A-2273584 and corresponding US Patent No. 5765186, the teachings of which are incorporated herein by reference.

5

10

15

20

The system 1 is operable in a number of different modes including an input mode when the system clock 10 is set at one rate and a preview mode

when the system clock is set at another rate. When operating in the input mode the system clock 10 is arranged to generate clocking signals appropriate to the 25/625 rate at which data is input from the VTR 5. As data is input from the VTR to the store 2, the data may also be output via the output buffer 14 for display of the image represented thereby on the monitor 15. The dynamics of the image are not correct when displayed in this mode because 25 frames are displayed in a period when only 24 frames should be displayed.

In the preview mode the system clock 10 is arranged to generate clocking signals appropriate to the display of data on the monitor 15 at a rate of 24 frames per second and 625 lines per frame (24/625). This corresponds to the frame rate at which the original images were captured on film and thus the dynamics of the scene are accurately represented. The monitor 15 shown in Figure 1 is a standard 25 frames per second monitor. Despite being designed for a frame rate of 25 frames per second, most, if not all, monitors currently available on the market can be adjusted (by varying the vertical sync signal) to display frames at a rate of 24 per second. Such an adjustment may be made manually by the operator or automatically by the system 1 depending on the particular monitor used.

Editing operations are effected at the 24 frames per second rate by the edit and control processor 12 in response to editor (user) manipulation of the stylus and touch tablet 13 with data movements within the system all occurring at a rate corresponding to the 24/625 rate. During the editing the

5

10

15

20

possible to convert to from an aspect ratio of 4:3 for standard PAL and NTSC to a wide screen aspect ratio of 16:9 by configuring the sizing circuit 11 to effect such a conversion. Such a conversion could equally be applied to a 25 frames per second output or a 30 frames per second output.

5           The invention is not limited to the 24 frames per second of movies, the 25 frames per second of PAL and the 30 frames per second of NTSC, or to the 625 lines of PAL and 525 lines of NTSC. Other standards can be achieved using the system 1 shown in Figure 1 by the appropriate modification of clocks and data rates.

10           The system 1 shown in Figure 1, whilst able to receive, manipulate and output data at different rates, is nevertheless restricted in that at any given time only one clock is running. Thus data cannot simultaneously be input at one data rate and output at another different data rate. Figure 2 of the accompanying drawings represents a system which addresses this and related  
15 issues.

Referring now to Figure 2, there is shown a system 21 having in common with the system 1 shown in Figure 1 many of the same elements. For the sake of conciseness elements which are equivalent to those of Figure 1 have been given the same reference numeral. The elements of Figure 2 will  
20 only be described insofar as they differ from the equivalent elements of Figure 1.

15

20

5

10

20

possible in part by the separation of the genlocked input and output operations 25, 29, and in part by the provision of the sizing circuit 11 and processor 26 which are able to process data " on the fly" as it is transferred from, over and to the asynchronous system bus.

5           Thus, for example, it is possible to combine video from a 24/1080 clip with a 25/625 clip to produce a combined clip which is output at, say, the 24/1080 clip by up-converting the 25/625 frames to 24/1080 frames as the data is output onto the system bus 24. By way of another example, if it is desired to convert a clip from 24 frames per second to 30 frames per second, 10 the processor 12 would be arranged to control the store 2 such that each frame of data is read out as two interleaved fields with the outputting one field of each frame being repeated to produce a 3:2 pull down, 30 frames per second version of the original 24 frames per second clip. Other combinations and conversions are, of course, also possible.

15           Having thus described the present invention by reference to a preferred embodiments it is to be well understood that the embodiments in question are exemplary only and that modifications and variations such as will occur to those possessed of appropriate knowledge and skills may be made without departure from the spirit and scope of the invention as set forth in the appended claims 20 and equivalents thereof.

006620-03900